

Known Models: Courier Spartan SSB
Pearce-Simpson Bengal SSB, Panther SSB
Regency CR-123, CR-123B

	Both RX & TX "A"	AM/USB Only "B"	LSB Only "C"		Both RX & TX "A"	AM/USB Only "B"	LSB Only "C"
Ch. 1 (26.965)	11.805	7.3615	7.3585	Ch.13 (27.115)	11.955	7.3615	7.3585
Ch. 2 (26.975)	"	7.3715	7.3685	Ch.14 (27.125)	"	7.3715	7.3685
Ch. 3 (26.985)	"	7.3815	7.3785	Ch.15 (27.135)	"	7.3815	7.3785
Ch. 4 (27.005)	"	7.4015	7.3985	Ch.16 (27.155)	"	7.4015	7.3985
Ch. 5 (27.015)	11.855	7.3615	7.3585	Ch.17 (27.165)	12.005	7.3615	7.3585
Ch. 6 (27.025)	"	7.3715	7.3685	Ch.18 (27.175)	"	7.3715	7.3685
Ch. 7 (27.035)	"	7.3815	7.3785	Ch.19 (27.185)	"	7.3815	7.3785
Ch. 8 (27.055)	"	7.4015	7.3985	Ch.20 (27.205)	"	7.4015	7.3985
Ch. 9 (27.065)	11.905	7.3615	7.3585	Ch.21 (27.215)	12.055	7.3615	7.3585
Ch.10 (27.075)	"	7.3715	7.3685	Ch.22 (27.225)	"	7.3715	7.3685
Ch.11 (27.085)	"	7.3815	7.3785	Ch.23 (27.255)	"	7.4015	7.3985
Ch.12 (27.105)	"	7.4015	7.3985				

Additional Crystals: 7.7985 MHz AM/USB Carrier Osc.
7.8015 MHz LSB Carrier Osc.
7.3435 MHz AM-only RX Oscillator

Synthesis: ["A" + "B" + 7.7985 MHz] = AM/USB carrier; ["A" + "C" + 7.8015 MHz] = LSB carrier

Compliments of:

CBC INTERNATIONAL · P.O. BOX 30655 · TUCSON AZ 85751 U.S.A.
TEL/FAX: 888-I-FIX-CBs (1-888-434-9227), (520) 298-7980 · Internet: www.cbcintl.com · Email: info@cbcintl.com