



## KL 300-24 linear amplifier

Schematic diagram

Version 4.10



**List of components**

C <sub>9</sub>	= 8,2 pF	50 V	NP0
C <sub>11</sub>	= 4,7 μF	16 V	
C <sub>12</sub>	= 33 μF	16 V	
C <sub>13</sub>	= 10 nF	50 V	
C <sub>14</sub>	= 10 nF	50 V	
C <sub>15</sub>	= 100 pF	50 V	NP0
C <sub>16</sub>	= 220 pF	50 V	N750
C <sub>17</sub>	= 270 pF	50 V	N750
C <sub>18</sub>	= 68 pF	500 V	NP0
C <sub>19</sub>	= 100 pF	500 V	NP0
C <sub>20</sub>	= 180 pF	500 V	N750
C <sub>21</sub>	= 120 pF	500 V	NP0
C <sub>23</sub>	= 270 pF	500 V	N750
C <sub>29</sub>	= 100 nF	50 V	
C <sub>30</sub>	= 47 μF	16 V	
C <sub>31</sub>	= 470 nF	100 V	Polyester
R <sub>8</sub>	= 2,2 KΩ	¼W	
R <sub>9</sub>	= 15 Ω	2W	
R <sub>10</sub>	= 100 Ω	2W	
R <sub>11</sub>	= 10 Ω	½W	
R <sub>20</sub>	= 1,0 KΩ	¼W	
D <sub>6</sub>	= 1N4148		
D <sub>7</sub>	= 1N4148		
D <sub>11</sub>	= 1N5400		
D <sub>13</sub>	= 1N4007		
Led <sub>1</sub>	= Led Rosso		
TR <sub>4</sub>	= BC 547		
TR <sub>5</sub>	= SD 1407		
L <sub>2</sub>	= 3 turns φ 8 mm wire φ 0,8 mm		ANRA 289
L <sub>3</sub>	= VK200		
L <sub>4</sub>	= 12 turns φ 6 mm wire φ 1 mm		ANRA 455
L <sub>5</sub>	= 4 turns φ 8 mm wire φ 1,2 mm		
RI <sub>1</sub>	= 0 Ω wire		
RI <sub>2</sub>	= Relè 24 V 3022		
Fuse	= 8A		